

# 650

## TV / VCR Cut-Off Timer



### Counter-Surveillance Device Cuts All Links to the Outside

- Easy to Use
- Easy to Install
- Functions on 110/220V, 50/60 Hz (voltage in = voltage out)
- Rugged Construction
- Top may be turned for wall-mount or TV-top use

The AES 650 Cut-Off Timer protects against electronic surveillance gained through a TV, VCR, cable box or any device connected to a cable or antenna and/or AC mains. These appliances are vulnerable because they are still powered even when they are turned "off".

By manually turning off the 650 Timer, or by allowing the built-in timer to elapse, the device disconnects both sides of the AC input and the cable/antenna input. This assures that the equipment is fully de-energized, and that the power and RF connections are cut to the outside world. The AES 650 also helps to protect the TV, VCR and other devices from electrical transients and storms.

The timer provides fail-secure operation: If the operator forgets to turn off the AES 650, the timer automatically disconnects the device after the time set, up to 6 hours.

#### Specifications

Size (approx): 5.50" x 8.25" x 3.75" - (14 x 21 x 9.5 cm)

Weight (approx): 4.2 pounds (1.9 kilograms)

Timer: 0-6 Hour, Variable, Spring Wound

Switched RF Input / Output - 75 ohm connectors, use with any cable or antenna input

AC Input: 110/220VAC, 50/60Hz, 6A, RFI Filtering

Switched AC Output: Voltage Output equals Voltage Input (this device does not convert voltage). BOTH sides of AC lines are switched.

Indicator: Amber, LED type. ON when timer is ON

**Ordering:** Order Part Number AES 650

#### AES Corporation

Call 1-800-237-6387

285 Newbury Street • Peabody, MA 01960 USA

Tel +1-978-535-7310 • Fax +1-978-535-7313

<http://www.aes-security.com>

